



Search Parameters:

[e-Catalog](#) > [Circuit Breakers](#) > Residential Circuit Breakers

Circuit Breakers, Residential Circuit Breakers

Product #: THQL21125

Short Description: 2 POLE 120/240V 10K IC 125 AMP

[Print This Page](#)

[Email This Page](#)

SPECIFICATIONS

Category	Feeder Plug-in Circuit Breakers
Trip Style	Non-Interchangeable
Frame Type	Q-Line
Amperage	125A
System Voltage	120 Vac , 120/240 Vac
Poles	2
Trip Function	LI
Continuous Current Rated	Standard
120 Vac Interrupting Rating	10 KAIC
120/240 Vac Interrupting Rating	10 KAIC
Suitable for Reverse Feed	Yes
Product Line	Q-Line (Plug-In)
UL File #	E11592
Long Time	Fixed
Instantaneous	Fixed
Protective Relays	No
Current Metering	No
Special Markings	HACR
GSA Compliance	Yes
GO Schedule	138A
UPC	078316408190
List Price	\$284



[View Larger](#)

Publications/Resources

[THQL21125](#)

Additional Resources for Feeder Plug-in Circuit Breakers

[Application and Technical](#)

[Installation and Instruction](#)

[Time Current Curves](#)

[Buy Log :1-45](#)

Q line circuit breakers are one-inch wide per pole, compact, thermal-magnetic devices designed for residential and commercial applications. The QL breakers are plug-in versions of the Q Line used for connection to load centers and lighting panels. All Q Line circuit breakers feature Quick-make / Quick-break mechanisms, common trip bars, and easy to spot trip indication to ensure safety and reliability. Q Line breakers are available in 1, 2, and 3 pole versions, can be ordered with auxiliary contact and shunt trip accessories, and can be ordered for use in HID applications.



ORLWIDE PARTNER